

# MAGEWELL

## Pro Convert Audio DX Technical Specifications

Copyright (c) 2011–2023 [Nanjing Magewell Electronics Co., Ltd.](http://www.magewell.com) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

NDI is trademark or registered trademark of NewTek Inc. Dante is registered trademarks of Audinate Pty Ltd. All other trademarks are the property of their respective owners.

Revised on 18/05/2023

### Receiving/Input Features

- Support for sample rates of 96/48/88.2/44.1 KHz, and 16/24bit sample depth
- 1 x 2-channel 3.5mm TRS unbalanced in (5k Ohm)
- 1 x 2-channel 4.4mm TRRRS balanced in (20k Ohm)
- 1 x 4-channel 24-bit/48k USB Audio Class in
- Receiving 8-channel 24-bit Dante® flows in unicast or multicast
- Receiving 2 x 4-channel 16-bit network audio streams of SRT and/or NDI® simultaneously
- Support for PTP master/slave
- Total harmonic distortion < 0.01% @ +4dBu
- Frequency Response 20Hz ~ 20kHz (-/+0.5dB)
- Signal to noise ratio > 100dB
- Dynamic range > 100dB
- Max signal level: unbalanced at 12dBu, balanced at 24dBu

### Transmitting/Output Features

- Support for sample rates of 96/48/88.2/44.1 KHz, and 16/24bit sample depth
- 1 x 2-channel 3.5mm TRS unbalanced out (10 Ohm)
- 1 x 2-channel 4.4mm TRRRS balanced out (150 Ohm)
- 1 x 4-channel 24-bit/48k UAC out
- Encoding 8-channel 24-bit Dante® flows in unicast or multicast
- Encoding 2 x 4-channel 16-bit network audio streams of RTSP, SRT, NDI® protocols simultaneously
- Support for PTP master/slave
- Total harmonic distortion < 0.01% @ +4dBu
- Frequency Response 20Hz ~ 20kHz (-/+0.5dB)
- Dynamic range > 100dB
- Signal to noise ratio > 100dB
- Max signal level: unbalanced at 12dBu, balanced at 18dBu

### Configuration Management

- Support for Dante Domain Manager and Dante Controller, providing signal routing and configuration
- Registration with Magewell Cloud
- Remote control via WebUI and Magewell Cloud
- Provision of comprehensive information regarding the device and signals in real-time
- Configuration of how an input is processed and codec, including volume setting, audio matrix, buffer, as well as the network connection
- Support for updating firmware
- Support for USB NET
- Support for IE/Edge/Firefox/Chrome/Safari/Opera web browsers
- Provision of HTTP APIs

### Interfaces

- 10/100/1000Mbps with PoE (IEEE 802.3af)
- USB2.0 Type B
  - 5V/2.1A power supply
  - USB NET
- 3.5mm TRS unbalanced IN/OUT
- 4.4mm TRRRS balanced IN/OUT

## LED Indicators

- Power LED indications:
  - on: power on
  - off: power off
- PTP LED indications:
  - on: synced
  - off: not synced
  - blinking: syncing

## Form Factor

- 100.9mm (L) x 60.2mm (W)x 23.3mm (H)

## Accessories

- 4.4mm to Dual XLR Male Cable
- 4.4mm to Dual XLR Female Cable
- USB 2.0 cable (Type A to Type B)
- Universal power adapter
- L bracket

## On-board Control Buttons

- 16 Position Rotary DIP Switch: set board-index from 0 to F

## Screw Mounting Hole

- ¼–20 threaded hole

## Power Consumption

- 5V max current: ~ 1 A
- Max power consumption: ~ 5 W

## Working Environment

- Operating temperature: 0 to 40 deg C
- Storage temperature: –20 to 70 deg C
- Relative humidity: 5% to 90% non-condensing